TA-F222ESR/F530ES

SERVICE MANUAL

Canadian Model
AEP Model
UK Model
TA-F530ES

E Model
TA-F222ESR

photo : TA-F530ES

SPECIFICATIONS

Amplifier section

Item	Condition		Data
Continuous RMS power outut (both channels driven simultaneously)	4 ohms, 20 Hz-20 kHz THD 0.008%	Canadian, UK, E model	120 W + 120 W (THD 0.01%) (DIN: 160 W + 160 W)
	6 ohms, 20 Hz-20 kHz THD 0.006%	Canadian, UK, E model	100 W + 100 W (DIN: 120 W + 120 W)
		AEP, West Germany model	95 W + 95 W (DIN: 115 W + 115 W)
	8 ohms, 20 Hz-20 kHz THD 0.004%	Canadian, UK, E model	90 W + 90 W (DIN: 110 W + 110 W)
		AEP, West Germany model	80 W + 80 W (DIN: 100 W + 100 W)
Power band width (IHF)	8 ohms, THD 0,02%		10 Hz - 100 kHz at 45 W
Dynamic headroom ('78 IHF)	4 ohms		2 dB
	8 ohms		1.2 dB
Total harmonic distortion	8 ohms, at 10 watt output		0.003%
Intermodulation (IM) distortion 60 Hz: 7 kHz = 4:1	4 ohm, at rated output		0.008%
	6 ohms at rated output		0.006%
	8 ohms at rated output		0.004%
Damping factor	8 ohms, 1 kHz		50
Residual noise	network A		less than 90μV
Frequency response	PHONO MM		RIAA equalization curve ±0.2 dB
	TUNER, CD, TAPE 1, 2, 3, DIRECT IN		2 Hz - 200 kHz $^{+0}_{-3}$ dB

—Continued on page 2—

使用時は添付資料も参照のこと
Refer to the additional documents.

INTEGRATED STEREO AMPLIFIER

SONY

Item	Condition		Data
Input sensitivity	PHONO	MC	0.17 mV, 100 ohms.
		MM	2.5 mV, 50 kohms
	TUNER, CD, DIRECT IN, TAPE 1, 2, 3 ADAPTOR IN		150 mV, 50 kohms
S/N (network)	PHONO	MC	68 dB 76 dB* (A)
		MM	80 dB 87 dB* (A)
*78 (IHF)	TUNER, CD, DIRECT IN, TAPE 1, 2, 3 ADAPTOR IN		84 dB 105 dB* (A)
Output voltage impedance	REC OUT 1, 2, 3 ADAPTOR OUT		150 mV, 1 kohm
	HEADPHONES		25 miliwatts (at 8 ohms) Accepts low and high impedance headphones.
Tone controls	BASS, at 100 Hz		±6 dB (turnover freq. 400 Hz)
	TREBLE, at 10 kHz		±6 dB (freq. 4 kHz)

General

System Preamplifier section: Low-noise high gain NFB type equalizer amplifier, passive type direct tone control
Power amplifier section: Pure-complementary SEPP power amplifier

Power requirements
AEP, West Germany model : 220 V AC, 50 Hz
U K model: 240 V AC, 50 Hz
E model : 120 V, 220 V or 240 V AC adjustable, 50/60 Hz
Canadian model : 120 V AC, 50/60Hz

Power consumption

Canadian model	510 VA
AEP, UK, West Germany model	220 W
UK model	600 W
E model	340 W

AC outlet

Canadian model	2 switched, 1 unswitched, 100 watts max. each
AEP, UK, West Germany model	—
E model	1 switched, 1 unswitched, 100 watts each

Dimensions

Approx. 430 x 150 x 370 mm (w/h/d)
(17 x 5 7/8 x 14 9/16 inches)

Weight

Approx. 13.5 kg (29 lbs 13 oz) net

MODEL IDENTIFICATION

– Specification Label –



Canadian model : AC 120V 60Hz
AEP, West Germany model : AC 220V~50/60Hz
UK model : AC 240V~50/60Hz
E model : AC 120/220/240V~50/60Hz

TABLE OF CONTENTS

SERVICING NOTES

On operating voltage

Before operating the unit, check that the operating voltage of your unit is identical with the voltage of your local power supply.

Where purchased	Operating voltage
UK Model	240 V AC
Canadian Model	120V AC
AEP, West Germany Model	220 V AC
E Model	120 V, 220 V or 240 V AC adjustable by AC voltage selector 

SAFETY-RELATED COMPONENT WARNING!!

COMPONENTS IDENTIFIED BY MARK ⚠ OR DOTTED LINE WITH MARK ⚠ ON THE SCHEMATIC DIAGRAMS AND IN THE PARTS LIST ARE CRITICAL TO SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY.

ATTENTION AU COMPOSANT AYANT RAPPORT À LA SÉCURITÉ!

LES COMPOSANTS IDENTIFIÉS PAR UNE MARQUE ⚠ SUR LES DIAGRAMMES SCHÉMATIQUES ET LA LISTE DES PIÈCES SONT CRITIQUES POUR LA SÉCURITÉ DE FONCTIONNEMENT. NE REMPLACER CES COMPOSANTS QUE PAR DES PIÈCES SONY DONT LES NUMÉROS SONT DONNÉS DANS CE MANUEL OU DANS LES SUPPLÉMENTS PUBLIÉS PAR SONY.

SAFETY CHECK-OUT

After correcting the original service problem, perform the following safety check before releasing the set to the customer:
Check the antenna terminals, metal trim, "metallized" knobs, screws, and all other exposed metal parts for AC leakage. Check leakage as described below.

LEAKAGE TEST

The AC leakage from any exposed metal part to earth ground and from all exposed metal parts to any exposed metal part having a return to chassis, must not exceed 0.5 mA (500 microampers). Leakage current can be measured by any one of three methods.

1. A commercial leakage tester, such as the Simpson 229 or RCA WT-540A. Follow the manufacturers' instructions to use these instruments.
2. A battery-operated AC milliammeter. The Data Precision 245 digital multimeter is suitable for this job.
3. Measuring the voltage drop across a resistor by means of a VOM or battery-operated AC voltmeter. The "limit" indication is 0.75 V, so analog meters must have an accurate low-voltage scale. The Simpson 250 and Sanwa SH-63Trd are examples of a passive VOM that is suitable. Nearly all battery operated digital multimeters that have a 2 V AC range are suitable. (See Fig. A)



Fig. A. Using an AC voltmeter to check AC leakage.

SECTION 1
GENERAL

PARTS IDENTIFICATION



[1] **POWER switch and power/standby indicator**
Immediately after turning ON the power, the standby indicator lights in red as the built-in muting circuit activates.
When the amplifier stays in a stable operating condition, the indicator lights in green.
The indicator lights in red when the unit detects shorting of circuit of the speaker outputs or in case of short-circuit of the inputs of DC components.
In such a case, disconnect the power source and check the connected components and speaker systems.

[2] **SPEAKERS selector**
Select speaker system A or B, or both.

[3] **ADAPTOR/DIRECT IN switch**
Set to NORMAL to select program source by INPUT SELECTOR. To listen to a program source processed through adapter (graphic equalizer, for example) connected to ADAPTOR jacks, set the selector to ADAPTOR.
To listen to a program source connected to DIRECT IN jacks, set it to DIRECT IN.
Note that selecting ADAPTOR has no effect upon the signals output through the REC OUT jacks.

[4] **INPUT SELECTOR**
Selects the desired program source.

[5] **ATTENUATOR knob**
Regulates the sound level.

[6] **MUTING switch and indicator**
Generally, keep the switch released (OFF).
Depress the switch to reduce the sound level by 20 dB. (Output voltage becomes 1/10.)

[7] **HEADPHONES jack (stereo phone jack)**

[8] **MODE selector**
STEREO: For listening to a stereo program.
MONO: For listening to a monaural program.

[9] **BASS and TREBLE controls**

[10] **REC OUT SELECTOR**
Selects the program source sent to the REC OUT jacks (rear panel).

[11] **BALANCE control**
Controls the sound level of left and right speakers.

[12] **SOURCE DIRECT switch and indicator**

[13] **CARTRIDGE selector**
Set the selector according to your cartridge.
MM: For moving-magnet type cartridge
MC: For moving-coil type cartridge

SECTION 2
ELECTRICAL ADJUSTMENTS

PRECAUTIONS

1. Adjust the idling after tuning the unit on for about 10-15 minutes, giving it time to warm up.

2. Always make sure to adjust the idling when repairing the power amp section or when replacing any parts.

【IDLING ADJUSTMENT】

Procedure :

Set the ATTENUATOR control as low as possible and adjust RT301 (L-CH) and RT351 (R-CH) so that the voltmeter reads 7mV at TP301 (L-CH) and TP351 (R-CH).

Adjustment Location: power board



SECTION 3
DIAGRAMS

CIRCUIT BOARD LOCATION



● Semiconductor Lead Layouts

STK-3102-3



2SA1215M-0
2SC2921M-0



2SA733-Q
2SA988-F
2SC945-P
2SC2545

2SA985A
2SC2275-P



2SC3423



2SD774-3

US1060M
UZL-16L
10E2N
30DF2



HZS-7B2L



SEL2510C



SEL2810A



3-1. PRINTED WIRING BOARDS

· See page 7 for Semiconductor Lead Layouts.

● Semiconductor Location

Ref. No.	Location	Ref. No.	Location
D201	J-11	IC301	I-30
D202	J-11	IC302	E-12
D203	J-1	IC401	E-30
D204	J-2		
D205	J-2	Q201	I-10
D206	J-1	Q202	J-12
D207	J-2	Q203	I-12
D208	G-19	Q204	I-11
D209	K-20	Q301	B-14
D301	E-17	Q302	C-14
D302	F-17	Q303	C-14
D303	F-15	Q304	B-13
D304	E-15	Q305	B-15
D305	E-18	Q306	C-12
D306	E-18	Q351	B-18
D307	E-14	Q352	C-18
D308	F-14	Q353	C-18
D309	E-14	Q354	B-19
D310	F-14	Q355	B-17
D311	E-14	Q356	C-20
D312	C-13	Q401	D-30
D313	C-12	Q402	D-30
D314	B-13	Q403	F-31
D319	B-7	Q404	F-21
D362	C-19	Q451	D-29
D363	C-20	Q452	D-29
D364	B-19		
D401	F-30		
D402	F-30		
D403	F-29		

Note on Printed Wiring Boards :

- ○—— : parts extracted from the component side.
- ■ : parts mounted on the conductor side.

[AC OUTLET BOARD]

[AC OUTLET BOARD]

[HP BOARD]

[POWER LED BOARD]

[SP JUMPER BOARD]

[SP TERMINAL BOARD]

[MAIN BOARD]

[SELECTOR BOARD]

[PINJACK(L) BOARD]

[PINJACK(S) BOARD]

[A/B JUMPER BOARD]

[MUTING BOARD]

[EQ BOARD]

3-2. SCHEMATIC DIAGRAMS



Note on Schematic Diagrams :

- All capacitors are in µF unless otherwise noted. pF: µµF 50WV or less are not indicated except for electrolytics and tantalums.
- All resistors are in Ω and 1/4 W or less unless otherwise specified.
- Components for right channel have same values as for left channel.
- [symbol] : nonflammable resistor.
- [symbol] : fusible resistor.

Note:	Note:
The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.	Les composants identifiés par une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

- [box] : adjustment for repair.
- Voltage and waveforms are dc with respect to ground under no-signal conditions.
  no mark : PHONO
- Voltages are taken with a VOM.
  (Input impedance 10M Ω)
  Voltage variations may be noted due to normal production torerances.
- Signal path.
  [arrow] : PHONO
- WG : West Germany
- CND : Canadian

SECTION 4
EXPLODED VIEWS

NOTE:

- The mechanical parts with no reference number in the exploded views are not supplied.
- The construction parts of an assembled part are indicated with a collation number in the remark column.
- Items marked "★" are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- Due to standardization, parts with part number suffix -XX and -X may be different from the parts specified in the components used on the set.
- Color Indication of Appearance Parts
  Example:
  (RED) ... KNOB, BALANCE (WHITE)
  ↑ ↑
  Cabinet's Color Parts' Color
- WG : West Germany model

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifiés par une marque ⚠ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

4-1. CABINET SECTION



No.	Part No.	Description	Remarks
1	4-908-875-01	KNOB, SQUARE	
2	4-929-227-01	JOINT	
3	4-864-307-00	RING	
4	4-929-224-01	KNOB (NA-48)	
5	4-916-745-01	KNOB (DIA.21)	
6	4-916-746-11	KNOB (DIA. 21), ROUND	
7	4-916-729-01	KNOB (DIA.29)	
8	4-908-856-01	KNOB, SQUARE	
9	A-4317-962-A	(Canadian)....PANEL ASSY, FRONT	
	A-4317-965-A	(AEP,WG,UK)...PANEL ASSY, FRONT	
	A-4323-063-A	(E).....PANEL ASSY, FRONT	
10	3-703-244-00	(Canadian,AEP,WG,UK)...BUSHING, CORD	
	3-703-571-11	(E).....BUSHING (S) (4516), CORD	
11	7-682-547-09	SCREW +BVTT 3X6 (S)	
12	4-885-984-21	(UK)...WASHER	
13	7-682-566-09	SCREW +B 4X20	
14	4-847-802-00	SCREW	
15	4-916-737-01	(Canadian,WG,UK,E)...CASE	
	4-916-737-21	(AEP).....CASE	

No.	Part No.	Description	Remarks
16	7-685-873-09	SCREW +BVTT 3X10 (S)	
17	*2-527-517-11	(UK)...CUSHION, CASE RETAINER	
18	*3-840-067-21	(UK)...SPACER (C)	
19	*4-929-232-01	SPACER	
20	3-706-165-00	SCREW	
21	*4-923-850-01	FOOT (DIA. 46)	
22	4-923-879-01	BUTTON (DIA.4)	
23	7-684-024-04	N 4, TYPE 2	
24	*4-929-266-01	CUSHION	
901	⚠1-551-478-00	(Canadian)...CORD, POWER	
	⚠1-574-381-11	(E).....CORD, POWER	
	⚠1-574-804-11	(UK).....CORD, POWER	
	⚠1-574-805-11	(AEP,WG).....CORD, POWER	
902	⚠1-526-565-00	(E)...AC PLUG ADAPTOR	
T1	⚠1-449-685-11	(Canadian)...TRANSFORMER, POWER	
T1	⚠1-449-687-11	(WG).....TRANSFORMER, POWER	
T1	⚠1-449-688-11	(AEP).....TRANSFORMER, POWER	
T1	⚠1-449-689-11	(UK).....TRANSFORMER, POWER	
T1	⚠1-449-690-11	(E).....TRANSFORMER, POWER	

4-2. CHASSIS SECTION



Note:	Note:
The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.	Les composants identifiés par une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

No.	Part No.	Description	Remarks
51	7-682-547-09	SCREW +BVTT 3X6 (S)	
52	7-685-647-79	SCREW +BVTP 3X10 TYPE2 N-S	
53	4-812-134-00	RIVET NYLON, 3.5	
54	*4-916-782-21	(UK)...DAMPER	
55	7-685-873-09	SCREW +BVTT 3X10 (S)	
56	*4-921-410-91	(UK)...CUSHION	
57	7-685-650-79	SCREW +BVTP 3X16 TYPE2 SLIT	
59	7-685-648-79	SCREW +BVTP 3X12 TYPE2 IT-3	
60	7-685-534-19	SCREW +BTP 2.6X8 TYPE2 N-S	
62	*4-929-233-03	(Canadian)...PANEL, BACK	
	*4-929-233-11	(WG,UK).....PANEL, BACK	
	*4-929-233-21	(AEP).....PANEL, BACK	
	*4-929-280-01	(E).....PANEL, BACK	
63	7-621-849-00	SCREW, TAPPING	
64	*4-916-782-61	(Canadian,UK)....DAMPER	
65	*4-921-410-81	(UK)....CUSHION	
66	*4-916-732-01	BOARD, BOTTOM	
67	7-685-876-09	SCREW +BVTT 3X16 (S)	
68	3-655-653-21	BAND (TAITON), BINDING	
69	*3-701-948-20	(E)...LABEL (T4A), FUSE	
70	*3-703-079-21	(Canadian)...LABEL, CAUTION (BACK)	
71	*3-703-270-00	(Canadian)...LABEL, AC 120V 60Hz	
72	*4-929-270-01	(Canadian)...LABEL, MODEL NUMBER	
	*4-929-272-01	(WG).....LABEL, MODEL NUMBER	
	*4-929-273-01	(UK).....LABEL, MODEL NUMBER	
	*4-929-274-01	(E).....LABEL, MODEL NUMBER	
	*4-931-906-01	(AEP).....LABEL, MODEL NUMBER	
73	*4-921-941-31	(UK)....CUSHION (FL)	
903	*1-629-749-11	PC BOARD, HP	
904	*1-629-751-11	PC BOARD, POWER LED	
905	*1-629-747-11	PC BOARD, MUTING	
906	*1-629-755-11	PC BOARD, AC OUTLET	
907	*1-629-753-11	PC BOARD, SP TERMINAL	
908	*1-629-757-11	PC BOARD, SP JUMPER	
909	*1-630-146-11	(Canadian)...PC BOARD, CLAMP	
910	*A-4333-335-A	(WG,E).....MOUNTED PCB, MAIN	
	*A-4333-343-A	(Canadian,AEP)...MOUNTED PCB, MAIN	
	*A-4333-725-A	(UK).....MOUNTED PCB, MAIN	
911	*1-629-750-11	PC BOARD, A/B JUMPER	
912	*1-629-758-11	PC BOARD, PINJACK (L)	
913	*1-629-756-11	PC BOARD, PIN JACK (S)	
914	*A-4333-336-A	(WG).....MOUNTED PCB, EQ	
	*A-4333-341-A	(AEP,E).....MOUNTED PCB, EQ	
	*A-4333-726-A	(UK).....MOUNTED PCB, EQ	
	*A-4358-218-A	(Canadian)...MOUNTED PCB, EQ	
915	*A-4410-898-A	(Canadian,WG,UK,E) ...MOUNTED PCB, SELECTOR	
916	1-533-190-11	(Canadian)...CLIP, FUSE	
917	1-533-183-11	(AEP,WG,UK,E)...HOLDER, FUSE	
C320	1-125-568-11	CAP, ELECT 12000MF	
C321	1-125-568-11	CAP, ELECT 12000MF	
C322	1-125-569-11	CAP, ELECT 5600MF	
C323	1-125-569-11	CAP, ELECT 5600MF	
CNJ501	⚠1-540-041-21	(E).....OUTLET, AC (AC OUTLET)	
CNJ501	⚠1-540-062-31	(Canadian)...OUTLET, AC (AC OUTLET)	
F501	⚠1-532-350-00	(E).....FUSE, TIME-LAG 4A	
F501	⚠1-532-510-00	(Canadian)....FUSE, GLASE TUBE 8A	
F502	⚠1-532-350-00	(E).....FUSE, TIME-LAG 4A	
F901	⚠1-532-350-00	(AEP,WG,UK)...FUSE, TIME-LAG 4A	
Q301	8-729-203-45	TRANSISTOR 2SC3423	
Q304	8-729-320-03	TRANSISTOR 2SC2921M-O	
Q305	8-729-320-01	TRANSISTOR 2SA1215M-O	
Q351	8-729-203-45	TRANSISTOR 2SC3423	
Q354	8-729-320-03	TRANSISTOR 2SC2921M-O	
Q355	8-729-320-01	TRANSISTOR 2SA1215M-O	
S501	⚠1-554-920-31	SWITCH, PUSH (AC POWER)(1 KEY)(POWER)	
S502	⚠1-570-307-11	(E)....SWITCH, VOLTAGE CHANGE (VOLTAGE SELECTOR)	

SECTION 5
ELECTRICAL PARTS LIST

NOTE:

- Due to standardization, replacements in the parts list may be different from the parts specified in the diagrams or the components used on the set.
- Items marked "★" are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- If there are two or more same circuits in a set such as a stereophonic machine, only typical circuit parts may be indicated and capacitors and resistors in other same circuits may be omitted.

CAPACITORS:
MF: μF, PF: μμF.

RESISTORS
- All resistors are in ohms.
- F: nonflammable

COILS
- MMH: mH, UH: μH

SEMICONDUCTORS
In each case, U: μ, for example:
UA...: μA..., UPA...: μPA..., UPC...: μPC, UPD...: μPD...

- WG : West Germany model

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifiés par une marque ⚠ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

Ref.No.	Part No.	Description
901	⚠1-551-478-00	(Canadian)...CORD, POWER
	⚠1-574-381-11	(E).....CORD, POWER
	⚠1-574-804-11	(UK).....CORD, POWER
	⚠1-574-805-11	(AEP,WG).....CORD, POWER
902	⚠1-526-565-00	(E).....AC PLUG ADAPTOR
903	*1-629-749-11	PC BOARD, HP
904	*1-629-751-11	PC BOARD, POWER LED
905	*1-629-747-11	PC BOARD, MUTING
906	*1-629-755-11	PC BOARD, AC OUTLET
907	*1-629-753-11	PC BOARD, SP TERMINAL
908	*1-629-757-11	PC BOARD, SP JUMPER
909	*1-630-146-11	(Canadian)...PC BOARD, CLAMP
910	*A-4333-335-A	(WG,E).....MOUNTED PCB, MAIN
	*A-4333-343-A	(Canadian,AEP)...MOUNTED PCB, MAIN
	*A-4333-725-A	(UK).....MOUNTED PCB, MAIN
911	*1-629-750-11	PC BOARD, A/B JUMPER
912	*1-629-758-11	PC BOARD, PINJACK (L)
913	*1-629-756-11	PC BOARD, PIN JACK (S)
914	*A-4333-336-A	(WG).....MOUNTED PCB, EQ
	*A-4333-341-A	(AEP,E).....MOUNTED PCB, EQ
	*A-4333-726-A	(UK).....MOUNTED PCB, EQ
	*A-4358-218-A	(Canadian)...MOUNTED PCB, EQ
915	*A-4410-898-A	(Canadian,WG,UK,E) ...MOUNTED PCB, SELECTOR
916	1-533-190-11	(Canadian)...CLIP, FUSE
917	1-533-183-11	(AEP,WG,UK,E)...HOLDER, FUSE
C101	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C102	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C103	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C104	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C105	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C106	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C108	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C109	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C151	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C152	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C153	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C154	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C155	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C156	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C158	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C159	1-162-284-31	(WG)...CERAMIC 150PF 10% 50V
C201	1-130-471-00	MYLAR 0.001MF 5% 50V
C202	1-130-478-00	MYLAR 0.0039MF 5% 50V
C203	1-130-479-00	MYLAR 0.0047MF 5% 50V
C204	1-136-159-00	FILM 0.033MF 5% 50V
C205	1-123-369-00	ELECT 4.7MF 20% 50V
C206	1-123-380-00	ELECT 1MF 20% 63V
C207	1-124-918-11	ELECT 47MF 20% 63V
C251	1-130-471-00	MYLAR 0.001MF 5% 50V
C252	1-130-478-00	MYLAR 0.0039MF 5% 50V
C253	1-130-479-00	MYLAR 0.0047MF 5% 50V
C254	1-136-159-00	FILM 0.033MF 5% 50V
C302	1-123-369-00	ELECT 4.7MF 20% 50V
C303	1-101-888-00	(E,AEP,WG)...CERAMIC 68PF 5% 50V
C303	1-104-276-00	(Canadian,UK) ...POLYSTYRENE 68PF 10% 50V
C304	1-123-360-00	(E,AEP,WG).....ELECT 100MF 20% 50V
C304	1-126-052-11	(Canadian,UK)...ELECT 100MF 20% 50V
C305	1-102-936-00	(E,AEP,WG)...CERAMIC 3PF 0.5PF 50V
C305	1-107-276-11	(Canadian,UK)...MICA 3PF 0.5% 500V
C306	1-123-369-00	(E,AEP,WG)...ELECT 4.7MF 20% 63V
C307	1-123-369-00	(E,AEP,WG)...ELECT 4.7MF 20% 63V
C308	1-102-951-00	(E,AEP,WG)...CERAMIC 15PF 5% 50V
C308	1-104-263-00	(Canadian,UK) ...POLYSTYRENE 15PF 10% 125V
C309	1-123-359-00	(E,AEP,WG,Canadian) ...ELECT 47MF 20% 50V
C309	1-124-910-11	(UK).....ELECT 47MF 20% 50V
C310	1-102-963-00	(E,AEP,WG,Canadian) ...CERAMIC 33PF 5% 50V
C310	1-107-159-00	(UK).....MICA 33PF 5% 500V
C311	1-102-963-00	(E,AEP,WG,Canadian) ...CERAMIC 33PF 5% 50V
C311	1-107-159-00	(UK).....MICA 33PF 5% 500V
C312	1-130-487-00	(E,WG,UK).....MYLAR 0.022MF 5% 50V
C312	1-136-161-00	(AEP,Canadian)...FILM 0.047MF 5% 50V
C313	1-130-471-00	MYLAR 0.001MF 5% 50V
C314	1-123-333-00	ELECT 100MF 20% 25V
C315	1-130-487-00	MYLAR 0.022MF 5% 50V
C317	1-123-333-00	ELECT 100MF 20% 25V
C318	1-123-604-00	ELECT 220MF 20% 63V
C319	1-123-379-00	ELECT 0.47MF 20% 100V
C320	1-125-568-11	CAP, ELECT 12000MF
C321	1-125-568-11	CAP, ELECT 12000MF
C322	1-125-569-11	CAP, ELECT 5600MF
C323	1-125-569-11	CAP, ELECT 5600MF

Ref.No.	Part No.	Description
C324	1-136-601-11	(E,AEP,WG,Canadian) ...FILM 0.01MF 10% 630V
C324	1-136-880-11	(UK).....FILM 2.2MF 10% 160V
C326	1-136-161-00	(AEP,Canadian)...FILM 0.047MF 5% 50V
C330	1-162-282-31	(WG).....CERAMIC 100PF 5% 50V
C331	1-102-973-00	(E,AEP,WG)...CERAMIC 100PF 5% 50V
C331	1-136-808-11	(UK,Canadian)...FILM 100MF 5% 100V
C333	1-161-370-00	(WG)...CERAMIC 0.01MF 30% 25V
C352	1-123-369-00	ELECT 4.7MF 20% 50V
C353	1-101-888-00	(E,AEP,WG)...CERAMIC 68PF 5% 50V
C353	1-104-276-00	(Canadian,UK) ...POLYSTYRENE 68PF 10% 50V
C354	1-123-360-00	(E,AEP,WG)...ELECT 100MF 20% 50V
C354	1-126-052-11	(Canadian,UK) ...ELECT 100PF 20% 50V
C355	1-102-936-00	(E,AEP,WG)...CERAMIC 3PF 0.5PF 50V
C355	1-107-276-11	(Canadian,UK)...MAIC 3PF 0.5PF 500V
C358	1-102-951-00	(E,AEP,WG)...CERAMIC 15PF 5% 50V
C358	1-104-263-00	(Canadian,UK) ...POLYSTYRENE 15PF 10% 125V
C359	1-123-359-00	(E,AEP,WG,Canadian) ...ELECT 47MF 20% 50V
C359	1-124-910-11	(UK).....ELECT 47MF 20% 50V
C360	1-102-963-00	(E,AEP,WG,Canadian) ...CERAMIC 33PF 5% 50V
C360	1-107-159-00	(UK).....MICA 33MF 5% 500V
C361	1-102-963-00	(E,AEP,WG,Canadian) ...CERAMIC 33PF 5% 50V
C361	1-107-159-00	(UK).....MICA 33MF 5% 500V
C362	1-130-487-00	(E,WG,UK)...MYLAR 0.022MF 5% 50V
C362	1-136-161-00	(AEP,Canadian) ...FILM 0.047MF 5% 50V
C376	1-136-161-00	(AEP,Canadian) ...FILM 0.047MF 5% 50V
C380	1-162-282-31	(WG)...CERAMIC 100PF 5% 50V
C381	1-102-973-00	(E,AEP,WG)...CERAMIC 100PF 5% 50V
C381	1-136-808-11	(Canadian,UK)...FILM 100PF 5% 100V
C401	1-101-361-00	(E,AEP).....CERAMIC 150PF 5% 50V
C401	1-102-112-00	(Canadian)...CERAMIC 330PF 10% 50V
C401	1-102-973-00	(WG).....CERAMIC 100PF 5% 50V
C401	1-104-282-11	(UK).....POLYSTYRENE 150PF 5% 50V
C402	1-123-369-00	ELECT 4.7MF 20% 50V
C403	1-124-472-11	(AEP,E,WG)...ELECT 470MF 20% 10V
C403	1-124-120-11	(Canadian)...ELECT 220MF 20% 16V
C403	1-126-103-11	(UK).....ELECT 470MF 20% 10V
C404	1-130-341-00	(UK,Canadian)...FILM 0.056MF 3% 100V
C404	1-136-162-00	(AEP,E,WG).....FILM 0.056MF 5% 50V
C405	1-130-971-00	(UK,Canadian)...FILM 0.016MF 3% 100V
C405	1-136-032-51	(AEP,E,WG).....FILM 0.016MF 5% 50V
C406	1-123-333-00	ELECT 100MF 20% 16V
C407	1-130-479-00	MYLAR 0.0047MF 5% 50V
C408	1-123-356-00	(E,AEP,WG)...ELECT 10MF 20% 50V
C408	1-123-380-00	(Canadian)...ELECT 1MF 20% 50V
C408	1-126-059-11	(UK).....ELECT 10MF 20% 50V
C409	1-123-359-00	(E,AEP,WG).....ELECT 47MF 20% 50V
C409	1-124-910-11	(UK,Canadian)...ELECT 47MF 20% 50V

Ref.No.	Part No.	Description
C410	1-123-359-00	(E,AEP,WG).....ELECT 47MF 20% 50V
C410	1-124-910-11	(UK,Canadian)...ELECT 47MF 20% 50V
C411	1-123-380-00	ELECT 1MF 20% 50V
C412	1-123-380-00	ELECT 1MF 20% 50V
C413	1-126-103-11	ELECT 470MF 20% 16V
C414	1-126-103-11	ELECT 470MF 20% 16V
C430	1-102-816-00	(WG)...CERAMIC 120PF 5% 50V
C431	1-162-282-31	(WG)...CERAMIC 100PF 5% 50V
C451	1-101-361-00	(E,AEP).....CERAMIC 150PF 5% 50V
C451	1-102-112-00	(Canadian)...CERAMIC 330PF 10% 50V
C451	1-102-973-00	(WG).....CERAMIC 100PF 5% 50V
C451	1-104-282-11	(UK).....POLYSTYRENE 150PF 5% 50V
C452	1-123-369-00	ELECT 4.7MF 20% 50V
C453	1-124-472-11	(E,AEP,WG)...ELECT 470MF 20% 10V
C453	1-124-120-11	(Canadian)...ELECT 220MF 20% 16V
C453	1-126-103-11	(UK).....ELECT 470MF 20% 10V
C454	1-130-341-00	(UK,Canadian)...FILM 0.056MF 3% 100V
C454	1-136-162-00	(E,AEP,WG).....FILM 0.056MF 5% 50V
C455	1-130-971-00	(UK,Canadian)...FILM 0.016MF 3% 100V
C455	1-136-032-51	(E,AEP,WG).....FILM 0.016MF 5% 50V
C457	1-130-479-00	MYLAR 0.0047MF 5% 50V
C458	1-123-356-00	(E,AEP,WG)...ELECT 10MF 20% 50V
C458	1-123-380-00	(Canadian)...ELECT 1MF 20% 50V
C458	1-126-059-11	(UK).....ELECT 10MF 20% 50V
C480	1-102-816-00	(WG)...CERAMIC 120PF 5% 50V
C481	1-162-282-31	(WG)...CERAMIC 100PF 5% 50V
C501	1-161-744-00	CERAMIC 0.01MF 400V
C902	1-136-153-00	(UK)...FILM 0.01MF 5% 50V
C903	1-136-153-00	(UK)...FILM 0.01MF 5% 50V
C904	1-102-978-00	(WG)...CERAMIC 220PF 5% 50V
C952	1-136-153-00	(UK)...FILM 0.01MF 5% 50V
C953	1-136-153-00	(UK)...FILM 0.01MF 5% 50V
C954	1-102-978-00	(WG)...CERAMIC 220PF 5% 50V
CN1	*1-561-651-00	SOCKET, CONNECTOR 7P
CN2	*1-561-651-00	SOCKET, CONNECTOR 7P
CN3	1-568-118-11	SOCKET, CONNECTOR 16P
CN4	*1-562-334-00	SOCKET, CONNECTOR 10P
CN5	*1-561-651-00	SOCKET, CONNECTOR 7P
CN6	1-568-203-11	PIN, CONNECTOR (PC BOARD) 11P
CN7	1-568-203-11	PIN, CONNECTOR (PC BOARD) 11P
CN8	*1-563-381-11	SOCKET, CONNECTOR 11P
CN9	*1-566-451-11	HOUSING, CONNECTOR 3P
CN10	*1-563-381-11	SOCKET, CONNECTOR 11P
CN11	1-568-117-11	SOCKET, CONNECTOR 14P
CN12	*1-565-484-11	CONNECTOR, BOARD TO BOARD 8P
CNJ501⚠1	-540-041-21	(E)....OUTLET, AC (AC OUT LET)
CNJ501⚠1	-540-062-31	(Canadian)...OUTLET, AC (AC OUT LET)
CNP604	*1-508-694-00	CONNECTOR PIN 8P
CP1	*1-560-532-00	PIN, CONNECTOR 7P
CP2	*1-560-532-00	PIN, CONNECTOR 7P
CP4	*1-568-202-11	PIN, CONNECTOR (PC BOARD) 10P

Note:
The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

Note:
Les composants identifiés par une marque ⚠ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

Ref.No.	Part No.	Description
CP5	1-568-120-11	PIN, CONNECTOR (PC BOARD) 7P
CP6	1-568-120-11	PIN, CONNECTOR (PC BOARD) 7P
CP7	*1-568-204-11	PIN, CONNECTOR (PC BOARD) 16P
D201	8-719-000-26	DIODE US1060M
D202	8-719-000-26	DIODE US1060M
D203	8-719-303-00	DIODE SEL2510C
D204	8-719-303-00	DIODE SEL2510C
D205	8-719-303-00	DIODE SEL2510C
D206	8-719-300-82	DIODE SEL2213C
D207	8-719-300-82	DIODE SEL2213C
D208	8-719-301-49	DIODE SEL2810A
D209	8-719-301-49	DIODE SEL2810A
D301	8-719-230-02	DIODE 30DF2
D302	8-719-230-02	DIODE 30DF2
D303	8-719-230-02	DIODE 30DF2
D304	8-719-230-02	DIODE 30DF2
D305	8-719-200-77	DIODE 10E2N
D306	8-719-200-77	DIODE 10E2N
D307	8-719-200-77	DIODE 10E2N
D308	8-719-200-77	DIODE 10E2N
D309	8-719-200-77	DIODE 10E2N
D310	8-719-200-77	DIODE 10E2N
D311	8-719-200-77	DIODE 10E2N
D312	8-719-000-26	DIODE US1060M
D313	8-719-000-26	DIODE US1060M
D314	8-719-000-26	DIODE US1060M
D319	8-719-000-26	DIODE US1060M
D362	8-719-000-26	DIODE US1060M
D363	8-719-000-26	DIODE US1060M
D364	8-719-000-26	DIODE US1060M
D401	8-719-933-47	DIODE HZS7B2L
D402	8-719-001-97	DIODE UZL-16L
D403	8-719-001-97	DIODE UZL-16L
EH2	*1-564-508-11	PLUG, CONNECTOR 5P
EH3	*1-564-508-11	PLUG, CONNECTOR 5P
F501	⚠1-532-350-00	(E).....FUSE, TIME-LAG 4A
F501	⚠1-532-510-00	(Canadian)....FUSE, GLASE TUBE 8A
F502	⚠1-532-350-00	(E).....FUSE, TIME-LAG 4A
F901	⚠1-532-350-00	(AEP,WG,UK)...FUSE, TIME-LAG 4A
IC301	8-749-920-70	IC STK3102-3
IC302	8-759-111-68	IC UPC1237HA
IC401	8-759-981-96	IC RC4560D
J101	1-565-320-51	JACK, PIN 6P (TUNER/CD/TAPE1,RECOUT)
J102	1-565-320-41	JACK, PIN 6P (TAPE2/REC OUT)
J103	1-565-320-51	JACK, PIN 6P (ADAPTOR IN,OUT/DIRECT IN)
J104	1-568-250-11	JACK, PIN 2P (PHONO)
L301	*1-420-872-00	(E,AEP,WG,UK)...COIL, AIR CORE
L301	*1-420-872-31	(Canadian).....COIL, AIR CORE
L351	*1-420-872-00	(E,AEP,WG,UK)...COIL, AIR CORE
L351	*1-420-872-31	(Canadian).....COIL, AIR CORE
L401	1-413-101-00	(WG)...COIL INPUT
L402	1-413-101-00	(WG)...COIL INPUT
L451	1-413-101-00	(WG)...COIL INPUT
L452	1-413-101-00	(WG)...COIL INPUT
Q201	8-729-177-42	TRANSISTOR 2SD774-3
Q202	8-729-194-57	TRANSISTOR 2SC945P
Q203	8-729-713-36	TRANSISTOR 2SA733Q

Ref.No.	Part No.	Description
Q204	8-729-713-36	TRANSISTOR 2SA733Q
Q301	8-729-203-45	TRANSISTOR 2SC3423
Q302	8-729-127-53	TRANSISTOR 2SC2275-P
Q303	8-729-190-53	TRANSISTOR 2SA985A
Q304	8-729-320-03	TRANSISTOR 2SC2921M-O
Q305	8-729-320-01	TRANSISTOR 2SA1215M-O
Q306	8-729-108-04	TRANSISTOR 2SA988F
Q351	8-729-203-45	TRANSISTOR 2SC3423
Q352	8-729-127-53	TRANSISTOR 2SC2275-P
Q353	8-729-190-53	TRANSISTOR 2SA985A-P
Q354	8-729-320-03	TRANSISTOR 2SC2921M-O
Q355	8-729-320-01	TRANSISTOR 2SA1215M-O
Q356	8-729-108-04	TRANSISTOR 2SA988F
Q401	8-729-354-52	TRANSISTOR 2SC2545
Q402	8-729-354-52	TRANSISTOR 2SC2545
Q403	8-729-194-57	TRANSISTOR 2SC945P
Q404	8-729-173-36	TRANSISTOR 2SA733Q
Q451	8-729-354-52	TRANSISTOR 2SC2545
Q452	8-729-354-52	TRANSISTOR 2SC2545
R000	1-247-725-11	CARBON 10K 5% 1/4W
R101	1-246-545-00	CARBON 1M 5% 1/4W
R102	1-246-545-00	CARBON 1M 5% 1/4W
R103	1-246-545-00	CARBON 1M 5% 1/4W
R104	1-246-545-00	CARBON 1M 5% 1/4W
R105	1-247-713-11	CARBON 1K 5% 1/4W
R106	1-249-417-11	CARBON 1K 5% 1/4W
R107	1-246-545-00	CARBON 1M 5% 1/4W
R108	1-246-545-00	CARBON 1M 5% 1/4W
R109	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R110	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R111	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R112	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R113	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R114	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R151	1-246-545-00	CARBON 1M 5% 1/4W
R152	1-246-545-00	CARBON 1M 5% 1/4W
R153	1-246-545-00	CARBON 1M 5% 1/4W
R154	1-246-545-00	CARBON 1M 5% 1/4W
R155	1-247-713-11	CARBON 1K 5% 1/4W
R156	1-249-417-11	CARBON 1K 5% 1/4W
R157	1-246-545-00	CARBON 1M 5% 1/4W
R158	1-246-545-00	CARBON 1M 5% 1/4W
R159	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R160	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R161	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R162	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R163	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R164	1-249-417-11	(WG)...CARBON 1K 5% 1/4W
R201	1-249-417-11	CARBON 1K 5% 1/4W
R202	1-247-700-11	CARBON 100 5% 1/4W
R203	1-247-717-11	CARBON 2.2K 5% 1/4W
R204	1-247-722-11	CARBON 5.6K 5% 1/4W
R205	1-249-753-15	CARBON 4.7M 5% 1/4W
R206	1-249-753-15	CARBON 4.7M 5% 1/4W
R208	1-247-170-00	CARBON 43K 5% 1/4W

Note:
The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

Note:
Les composants identifiés par une marque ⚠ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

Ref.No.	Part No.	Description				
R209	1-247-152-00	CARBON	7.5K	5%	1/4W	
R210	1-249-464-11	CARBON	39K	5%	1/4W	
R211	1-249-465-11	CARBON	47K	5%	1/4W	
R212	1-249-465-11	CARBON	47K	5%	1/4W	
R213	1-247-722-11	CARBON	5.6K	5%	1/4W	
R214	1-247-693-11	CARBON	27	5%	1/4W	
R215	1-247-754-11	CARBON	1.5K	5%	1/2W	
R216	1-247-754-11	CARBON	1.5K	5%	1/2W	
R217	1-247-750-11	CARBON	680	5%	1/2W	
R218	1-249-462-11	CARBON	22K	5%	1/4W	
R219	1-249-465-11	CARBON	47K	5%	1/4W	
R220	1-247-749-11	CARBON	560	5%	1/2W	
R221	1-247-717-11	CARBON	2.2K	5%	1/4W	
R222	1-247-725-11	CARBON	10K	5%	1/4W	
R223	1-249-465-11	CARBON	47K	5%	1/4W	
R224	1-247-721-11	CARBON	4.7K	5%	1/4W	
R225	1-247-752-11	CARBON	1K	5%	1/2W	
R226	1-247-752-11	CARBON	1K	5%	1/2W	
R227	1-247-752-11	(E,WG,Canadian,UK) ...CARBON	1K	5%	1/2W	
R227	1-247-239-00	(AEP)...CARBON	910	5%	1/2W	
R228	1-247-752-11	(E,WG,Canadian,UK) ...CARBON	1K	5%	1/2W	
R228	1-247-239-00	(AEP)...CARBON	910	5%	1/2W	
R251	1-249-417-11	CARBON	1K	5%	1/4W	
R252	1-247-700-11	CARBON	100	5%	1/4W	
R253	1-247-717-11	CARBON	2.2K	5%	1/4W	
R254	1-247-722-11	CARBON	5.6K	5%	1/4W	
R255	1-249-753-15	CARBON	4.7M	5%	1/4W	
R256	1-249-753-15	CARBON	4.7M	5%	1/4W	
R258	1-247-170-00	CARBON	43K	5%	1/4W	
R259	1-247-152-00	CARBON	7.5K	5%	1/4W	
R260	1-249-464-11	CARBON	39K	5%	1/4W	
R261	1-249-465-11	CARBON	47K	5%	1/4W	
R262	1-249-465-11	CARBON	47K	5%	1/4W	
R263	1-247-722-11	CARBON	5.6K	5%	1/4W	
R301	1-247-713-11	CARBON	1K	5%	1/4W	
R302	1-249-599-11	CARBON	91K	5%	1/4W	
R303	1-249-668-11	CARBON	620	5%	1/2W	
R304	1-247-713-11	CARBON	1K	5%	1/4W	
R305	1-247-707-11	CARBON	390	5%	1/4W	
R306 ⚠	1-212-990-00	FUSIBLE	220	5%	1/2W	F
R307 ⚠	1-212-950-00	FUSIBLE	4.7	5%	1/2W	F
R308 ⚠	1-212-950-00	FUSIBLE	4.7	5%	1/2W	F
R309	1-217-611-00	METAL PLATE	0.1	10%	2W	
R310	1-217-611-00	METAL PLATE	0.1	10%	2W	
R311 ⚠	1-247-717-11	CARBON	2.2K	5%	1/4W	F
R312	1-249-460-11	CARBON	15K	5%	1/4W	
R313 ⚠	1-212-962-00	FUSIBLE	15	5%	1/2W	F
R314 ⚠	1-212-962-00	FUSIBLE	15	5%	1/2W	F
R315	1-247-891-00	CARBON	330K	5%	1/4W	
R316	1-247-725-11	CARBON	10K	5%	1/4W	
R317	1-247-887-00	CARBON	220K	5%	1/4W	
R318	1-247-881-00	CARBON	120K	5%	1/4W	
R319	1-249-461-11	CARBON	18K	5%	1/4W	
R320	1-247-721-11	CARBON	4.7K	5%	1/4W	
R321	1-249-462-11	CARBON	22K	5%	1/4W	
R323 ⚠	1-212-849-00	FUSIBLE	4.7	5%	1/4W	F
R324	1-247-727-11	CARBON	10	5%	1/2W	
R325	1-247-747-11	CARBON	470	5%	1/2W	

Ref.No.	Part No.	Description				
R326	1-249-721-11	CARBON	100K	5%	1/2W	
R327	1-247-708-11	CARBON	470	5%	1/4W	
R351	1-247-713-11	CARBON	1K	5%	1/4W	
R352	1-249-599-11	CARBON	91K	5%	1/4W	
R353	1-249-668-11	CARBON	620	5%	1/2W	
R354	1-247-713-11	CARBON	1K	5%	1/4W	
R355	1-247-707-11	CARBON	390	5%	1/4W	
R356 ⚠	1-212-990-00	FUSIBLE	220	5%	1/2W	F
R357 ⚠	1-212-950-00	FUSIBLE	4.7	5%	1/2W	F
R358 ⚠	1-212-950-00	FUSIBLE	4.7	5%	1/2W	F
R359	1-217-611-00	METAL PLATE	0.1	10%	2W	
R360	1-217-611-00	METAL PLATE	0.1	10%	2W	
R361 ⚠	1-247-717-11	CARBON	2.2K	5%	1/4W	F
R362	1-249-460-11	CARBON	15K	5%	1/4W	
R363 ⚠	1-212-962-00	FUSIBLE	15	5%	1/2W	F
R364 ⚠	1-212-962-00	FUSIBLE	15	5%	1/2W	F
R365	1-247-891-00	CARBON	330K	5%	1/4W	
R374	1-247-727-11	CARBON	10	5%	1/2W	
R375	1-247-747-11	CARBON	470	5%	1/2W	
R376	1-249-721-11	CARBON	100K	5%	1/2W	
R377	1-247-708-11	CARBON	470	5%	1/4W	
R401 ⚠	1-216-459-00	METAL OXIDE	2.7K	5%	2W	F
R402 ⚠	1-215-895-11	METAL OXIDE	3.3K	5%	2W	F
R403	1-247-721-11	CARBON	4.7K	5%	1/4W	
R404	1-247-721-11	CARBON	4.7K	5%	1/4W	
R405	1-247-706-11	(E,AEP,UK,Canadian) ...CARBON	330	5%	1/4W	
R406	1-249-469-11	CARBON	100K	5%	1/4W	
R407	1-247-700-11	CARBON	100	5%	1/4W	
R408	1-249-469-11	CARBON	100K	5%	1/4W	
R409	1-247-713-11	CARBON	1K	5%	1/4W	
R410	1-247-713-11	CARBON	1K	5%	1/4W	
R411	1-247-725-11	CARBON	10K	5%	1/4W	
R412	1-249-484-11	CARBON	6.8	5%	1/2W	
R413	1-247-739-11	CARBON	100	5%	1/2W	
R414	1-247-138-00	CARBON	2K	5%	1/4W	
R415	1-247-700-11	CARBON	100	5%	1/4W	
R416	1-214-937-00	CARBON	1M	5%	1/2W	
R417	1-249-844-11	CARBON	56K	5%	1/2W	
R418	1-249-818-11	CARBON	4.7K	1%	1/2W	
R419	1-247-713-11	CARBON	1K	5%	1/4W	
R431	1-247-713-11	(WG)...CARBON	1K	5%	1/4W	
R432	1-247-713-11	(WG)...CARBON	1K	5%	1/4W	
R455	1-247-706-11	(E,AEP,UK,Canadian) ...CARBON	330	5%	1/4W	
R456	1-249-469-11	CARBON	100K	5%	1/4W	
R457	1-247-700-11	CARBON	100	5%	1/4W	
R458	1-249-469-11	CARBON	100K	5%	1/4W	
R459	1-247-713-11	CARBON	1K	5%	1/4W	
R460	1-247-713-11	CARBON	1K	5%	1/4W	
R461	1-247-725-11	CARBON	10K	5%	1/4W	
R462	1-249-484-11	CARBON	6.8	5%	1/2W	
R463	1-247-739-11	CARBON	100	5%	1/2W	
R465	1-247-700-11	CARBON	100	5%	1/4W	

Note:
The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

Note:
Les composants identifiés par une marque ⚠ sont critiques pour la sécurité.
Ne les remplacer que par une pièce portant le numéro spécifié.

Ref.No.	Part No.	Description
R466	1-214-937-00	CARBON 1M 5% 1/2W
R467	1-249-844-11	CARBON 56K 5% 1/2W
R468	1-249-818-11	CARBON 4.7K 1% 1/2W
R469	1-247-713-11	CARBON 1K 5% 1/4W
R481	1-247-713-11	(WG)...CARBON 1K 5% 1/4W
R482	1-247-713-11	(WG)...CARBON 1K 5% 1/4W
R902	1-247-727-11	(WG)...CARBON 10 5% 1/2W
R903	1-247-727-11	(WG)...CARBON 10 5% 1/2W
RT301	1-237-455-11	RES, ADJ, CARBON 500
RT351	1-237-455-11	RES, ADJ, CARBON 500
RV101	1-238-448-11	RES, VAR, CARBON 150K/150K (BALANCE)
RV102	1-238-446-11	RES, VAR, CARBON 250K/250K (TREBLE)
RV103	1-238-447-11	RES, VAR, CARBON 25K/500K (BASS)
RV104	1-237-472-11	RES, VAR, CARBON 120K/120K(ATTENUATOR)
RY301	1-515-501-00	RELAY
S201	1-571-824-11	SWITCH, ROTARY (INPUT SELECTOR)
S202	1-571-826-11	SWITCH, ROTARY (INPUT SELECTOR)
S203	1-571-823-11	SWITCH, ROTARY SLIDE(REC OUT SELECTOR)
S204	1-571-828-11	SWITCH, PUSH (1 KEY)(SOURCE DIRECT)
S205	1-571-827-11	SWITCH, PUSH (1 KEY)(MUTING)
S206	1-571-822-11	SWITCH, ROTARY SLIDE (SPEAKER)
S207	1-571-825-11	SWITCH, ROTARY (MODE)
S401	1-571-111-11	SWITCH, PUSH (1 KEY)(CARTRIDGE)
S501	⚠1-554-920-31	SWITCH, PUSH (AC POWER)(1 KEY)(POWER)
S502	⚠1-570-307-11	(E)...SWITCH, VOLTAGE CHANGE (VOLTAGE SELECTOR)
T1	⚠1-449-685-11	(Canadian)...TRANSFORMER, POWER
T1	⚠1-449-687-11	(WG).....TRANSFORMER, POWER
T1	⚠1-449-688-11	(AEP).....TRANSFORMER, POWER
T1	⚠1-449-689-11	(UK).....TRANSFORMER, POWER
T1	⚠1-449-690-11	(E).....TRANSFORMER, POWER
TM501	1-537-235-11	TERMINAL BOARD (SP)
TP301	1-535-135-00	BASE POST 14MM (10MM PITCH) 2P
TP351	1-535-135-00	BASE POST 14MM (10MM PITCH) 2P
VH2	*1-564-321-00	PIN, CONNECTOR 2P
VH3	1-564-320-00	PIN, CONNECTOR 2P
VH4	*1-564-321-00	(AEP,UK,WG)....PIN, CONNECTOR 2P
VH5	*1-565-792-11	PIN, CONNECTOR 2P
VH6	*1-564-321-00	(AEP,UK,WG)....PIN, CONNECTOR 2P
VH8	*1-564-241-00	PIN, CONNECTOR 4P
VH9	*1-560-595-21	TERMINAL (WITH BASE)
VH11	1-564-321-00	(Canadian,E)...PIN, CONNECTOR 2P
VH12	1-564-320-00	PIN, CONNECTOR 2P
VH20	*1-535-141-00	(E)...BASE POST 22MM (10MM PITCH) 4P
		ACCESSORY & PACKING MATERIAL
	3-786-976-11	(Canadian,UK,E)...MANUAL, INSTRUCTION
	3-786-976-41	(AEP,WG).....MANUAL, INSTRUCTION
	*4-929-219-01	CUSHION
	*4-929-263-11	INDIVIDUAL CARTON

Note: The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.	**Note:** Les composants identifiés par une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

9-953-786-11

Sony Corporation
Audio Group

English
89E1648-1
Printed in Japan

Published by A/V Engineering Service Dept.

TA-F222ESR/F530ES

SONY

SERVICE MANUAL

Canadian Model
AEP Model
UK Model
TA-F530ES
E Model
TA-F222ESR

SUPPLEMENT-1

File this Supplement with the Service Manual (9-953-786-11).

Subject : Boards change

Part number suffix of boards have been changed as shown below.

• AC OUTLET BOARD	1-629-755-15
• EQ BOARD	1-629-748-17
• MAIN BOARD	1-629-754-15
• MUTING BOARD	1-629-747-12
• PIN JACK (S) BOARD	1-629-756-14
• SELECTOR BOARD	1-629-746-14
• SP JUMPER BOARD	1-629-757-13
• SP TERMINAL BOARD	1-629-753-17

SECTION 3
DIAGRAMS

3-1. PRINTED WIRING BOARDS

• Semiconductor Location

Ref. No.	Location	Ref. No.	Location
D201	J-11	IC301	I-30
D202	J-11	IC302	E-12
D203	J-1	IC401	E-30
D204	J-2	IC402	G-31
D205	J-2	IC403	G-29
D206	J-1		
D207	J-2	Q201	I-10
D208	G-19	Q202	J-12
D209	K-20	Q203	I-12
D301	E-17	Q204	I-11
D302	F-17	Q301	B-14
D303	F-15	Q302	C-14
D304	E-15	Q305	B-15
D305	E-18	Q306	C-12
D306	E-18	Q351	B-18
D307	E-14	Q352	C-18
D308	F-14	Q353	C-18
D309	E-14	Q354	B-19
D310	F-14	Q355	B-17
D311	E-14	Q356	C-20
D312	C-13	Q401	D-30
D313	C-12	Q402	D-30
D314	B-13	Q403	F-31
D319	D-7	Q404	F-21
D320	D-8	Q451	D-29
D362	C-19	Q452	D-29
D363	C-20		
D364	B-19		
D401	F-30		



Note on Printed Wiring Boards:

- ⏀—— : parts extracted from the components side.
- ■ : parts mounted on the conductor side.
- ⁘⁘⁘ : Pattern on the side which is seen.
- G : German model

Note :
There are two typed of AEP models which are depend on countries.
AEP2 model : Model for Scandinavian countries, Switzerland, Finland.
AEP1 model : Model for other European countries.



Note Note on Schematic Diagrams:

- All capacitors are in μF unless otherwise noted. pF=μμF 50WV or less are not indicated except for electrolytics and tantalums.
- All resistors are in Ω and 1/4W or less unless otherwise specified.
- Components for right channel have same values as for left channel.
- : nonflammable resistor.
- : fusible resistor.

Note:	**Note:**
The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.	Les composants identifiés par une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une pièce portant le numéro spécifié.

- B+ Line
- B- Line
- : adjustment for repair.
- Voltage and waveforms are dc with respect to ground under no-signal conditions. no mark: PHONO
- Voltages are taken with a VOM. (Input impedance 10MΩ) Voltage variations may be noted due to normal production tolerances.
- Signal path. : PHONO
- CND : Cambodia model

Note :
There are two typed of AEP models which are depend on countries.
AEP2 model : Model for Scandinavian countries, Switzerland, Finland.
AEP1 model : Model for other European countries.

SECTION 5
ELECTRICAL PARTS LIST

NOTE:

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety.
Replace only with part number specified.

Les composants identifiés par une marque ⚠ sont critiques pour la sécurité.
Ne les remplacer que par une piéce portant le numéro spécifié.

When indicating parts by reference number, please include the board name.

- Items marked "*" are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.
- RESISTORS
  All resistors are in ohms
  METAL: Metal-film resistor
  METAL OXIDE: Metal Oxide-film resistor
  F : nonflammable
- SEMICONDUCTORS
  In each case, u: μ , for example:
  uA...: μA..., uPA...: μPA..., uPB...: μPB..., uPC...: μPC..., uPD...: μPD...
- CAPACITORS
  uF : μF
- COILS
  uH : μH
- -XX, -X mean standardized parts, so they may have some difference from the original one.
- Due to standardization, replacements in the parts list may be different from the parts specified in the diagrams or the components used on the set.
- G: German model

Note:
There are two type of AEP models which are depend on countries.
AEP2 model: Model for Scandinavian countries. Switzerland, Finland.
AEP1 model: Model for other European countries.

Ref. No.	Part No.	Description	Remark
⚠901	1-551-478-00	CORD, POWER (Canadian)	
⚠901	1-574-381-11	CORD, POWER (E)	
⚠901	1-574-804-11	CORD, POWER (UK)	
⚠901	1-574-805-11	CORD, POWER (AEP, G)	
⚠902	1-526-565-00	AC PLUG ADAPTOR (E)	
* 903	1-629-749-11	PC BOARD, HP	
* 904	1-629-751-11	PC BOARD, POWER LED	
* 905	1-629-747-11	PC BOARD, MUTING	
* 906	1-629-755-11	PC BOARD, AC OUTLET (Canadian, E)	
* 907	1-629-753-11	PC BOARD, SP TERMINAL	
* 908	1-629-757-11	PC BOARD, SP JUMPER	
* 909	1-630-146-11	PC BOARD, CLAMP (Canadian)	
* 910	A-4333-335-A	MOUNTED PCB, MAIN (AEP1, G, E)	
* 910	A-4333-343-A	MOUNTED PCB, MAIN (Canadian, AEP2)	
* 910	A-4333-725-A	MOUNTED PCB, MAIN (UK)	
* 911	1-629-750-11	PC BOARD, A/B JUMPER	
* 912	1-629-758-11	PC BOARD, PIN JACK (L)	
* 913	1-629-756-11	PC BOARD, PIN JACK (S)	
* 914	A-4333-336-A	MOUNTED PCB, EQ (G)	
* 914	A-4333-341-A	MOUNTED PCB, EQ (Canadian, AEP, E)	
* 914	A-4333-726-A	MOUNTED PCB, EQ (UK)	
* 915	A-4410-898-A	MOUNTED PCB, SELECTOR (Canadian, AEP1, G, UK, E)	
* 915	A-4333-344-A	MOUNTED PCB, SELECTOR (AEP2)	
916	1-533-190-11	CLIP, FUSE (Canadian)	
917	1-533-183-11	HOLDER, FUSE (AEP, G, UK, E)	

< CAPACITOR >

Ref. No.	Part No.	Description			Remark
C101	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C102	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C103	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C104	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C105	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C106	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C108	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C109	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C110	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C151	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C152	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C153	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C154	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C155	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C156	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C158	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C159	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C160	1-162-284-31	CERAMIC	150PF	10%	50V (G)
C201	1-130-471-00	MYLAR	0.001uF	5%	50V
C202	1-130-478-00	MYLAR	0.0039uF	5%	50V
C203	1-130-479-00	MYLAR	0.0047uF	5%	50V
C204	1-136-159-00	FILM	0.033uF	5%	50V
C205	1-123-369-00	ELECT	4.7uF	20%	50V
C206	1-124-791-11	ELECT	1.0uF	20%	100V
C207	1-124-918-11	ELECT	47uF	20%	63V
C251	1-130-471-00	MYLAR	0.001uF	5%	50V
C252	1-130-478-00	MYLAR	0.0039uF	5%	50V
C253	1-130-479-00	MYLAR	0.0047uF	5%	50V
C254	1-136-159-00	FILM	0.033uF	5%	50V
C302	1-123-369-00	ELECT	4.7uF	20%	50V
C303	1-101-888-00	CERAMIC	68PF	5%	50V (Canadian, E, AEP, G)
C303	1-104-276-11	POLYSTYRENE	68PF	10%	50V (UK)
C304	1-124-572-11	ELECT	100uF	20%	63V (Canadian, E, AEP, G)
C304	1-126-052-11	ELECT	100uF	20%	50V (UK)
C305	1-102-936-00	CERAMIC	3.0PF	+-0.25PF	50V (Canadian, E, AEP, G)
C305	1-107-044-00	MICA	3PF	5%	500V (UK)
C306	1-123-369-00	ELECT	4.7uF	20%	63V
C307	1-123-369-00	ELECT	4.7uF	20%	63V
C308	1-102-951-00	CERAMIC	15PF	5%	50V (Canadian, E, AEP, G)
C308	1-104-263-00	POLYSTYRENE	15PF	10%	125V (UK)
C309	1-124-910-11	ELECT	47uF	20%	50V (UK)
C309	1-124-918-11	ELECT	47uF	20%	63V (Canadian, E, AEP, G)
C310	1-102-963-00	CERAMIC	33PF	5%	50V (Canadian, E, AEP, G)
C310	1-107-159-00	MICA	33PF	5%	500V (UK)
C311	1-102-963-00	CERAMIC	33PF	5%	50V (Canadian, E, AEP, G)
C311	1-107-159-00	MICA	33PF	5%	500V (UK)
C312	1-130-487-00	MYLAR	0.022uF	5%	50V (E, AEP1, UK, G)
C312	1-136-161-00	FILM	0.047uF	5%	50V (Canadian, AEP2)
C313	1-130-471-00	MYLAR	0.001uF	5%	50V
C314	1-124-122-11	ELECT	100uF	20%	50V

Ref.No.	Part No.	Description				Remark
C315	1-130-487-00	MYLAR	0.022uF	5%	50V	
C317	1-124-122-11	ELECT	100uF	20%	50V	
C318	1-123-604-00	ELECT	220uF	20%	63V	
C319	1-123-379-00	ELECT	0.47uF	20%	100V	
C320	1-125-460-11	ELECT.	12000uF			
C321	1-125-460-11	ELECT	12000uF			
C322	1-125-558-11	ELECT	5600uF			
C323	1-125-558-11	ELECT	5600uF			
C324	1-136-601-11	FILM	0.01uF	10%	630V	
						(Canadian, E, AEP, G)
C324	1-136-880-11	FILM	2.2uF	10%	160V (UK)	
C326	1-136-161-00	FILM	0.047uF	5%	50V	
						(Canadian, AEP2)
C330	1-162-282-31	CERAMIC	100PF	5%	50V (G)	
C331	1-102-973-00	CERAMIC	100PF	5%	50V	
						(Canadian, E, AEP, G)
C331	1-136-808-11	FILM	100PF	5%	100V (UK)	
C333	1-161-379-00	CERAMIC	0.01uF	30%	25V (G)	
C352	1-123-369-00	ELECT	4.7uF	20%	50V	
C353	1-101-888-00	CERAMIC	68PF	5%	50V	
						(Canadian, E, AEP, G)
C353	1-104-276-11	POLYSTYRENE	68PF	10%	50V (UK)	
C354	1-124-572-11	ELECT	100uF	20%	63V	
						(Canadian, E, AEP, G)
C354	1-126-052-11	ELECT	100uF	20%	50V (UK)	
C355	1-102-936-00	CERAMIC	3.0PF	+-0.25PF	50V	
						(Canadian, E, AEP, G)
C355	1-107-044-00	MICA	3PF	0.5PF	500V (UK)	
C358	1-102-951-00	CERAMIC	15PF	5%	50V	
						(Canadian, E, AEP, G)
C358	1-104-263-00	POLYSTYRENE	15PF	10%	125V (UK)	
C359	1-124-910-11	ELECT	47uF	20%	50V (UK)	
C359	1-124-918-11	ELECT	47uF	20%	63V	
						(Canadian, E, AEP, G)
C360	1-102-963-00	CERAMIC	33PF	5%	50V	
						(Canadian, E, AEP, G)
C360	1-107-159-00	MICA	33PF	5%	500V (UK)	
C361	1-102-963-00	CERAMIC	33PF	5%	50V	
						(Canadian, E, AEP, G)
C361	1-107-159-00	MICA	33PF	5%	500V (UK)	
C362	1-130-487-00	MYLAR	0.022uF	5%	50V	
						(E, AEP1, UK, G)
C362	1-136-161-00	FILM	0.047uF	5%	50V	
						(Canadian, AEP2)
C376	1-136-161-00	FILM	0.047uF	5%	50V	
						(Canadian, AEP)
C380	1-162-282-31	CERAMIC	100PF	5%	50V (G)	
C381	1-102-973-00	CERAMIC	100PF	5%	50V	
						(Canadian, E, AEP, G)
C381	1-136-808-11	FILM	100pF	5%	100V (UK)	
C401	1-101-361-00	CERAMIC	150PF	5%	50V	
						(Canadian, E, AEP)
C401	1-102-973-00	CERAMIC	100PF	5%	50V (G)	

Ref.No.	Part No.	Description				Remark
C401	1-104-282-11	POLYSTYRENE	150PF	5%	50V (UK)	
C402	1-123-369-00	ELECT	4.7uF	20%	50V	
C403	1-124-472-11	ELECT	470uF	20%	10V	
						(Canadian, E, AEP)
C403	1-126-103-11	ELECT	470uF	20%	10V (UK, G)	
C404	1-130-341-00	FILM	0.056uF	3%	100V (UK)	
C404	1-136-162-00	FILM	0.056uF	5%	50V	
						(Canadian, E, AEP, G)
C405	1-130-971-00	FILM	0.016uF	3%	100V (UK)	
C405	1-136-032-11	FILM	0.016uF	5%	50V	
						(Canadian, E, AEP, G)
C406	1-124-122-11	ELECT	100uF	20%	50V	
C407	1-130-479-00	MYLAR	0.0047uF	5%	50V	
C408	1-124-915-11	ELECT	10uF	20%	63V	
						(Canadian, E, AEP, G)
C408	1-126-059-11	ELECT	10uF	20%	50V (UK)	
C409	1-124-910-11	ELECT	47uF	20%	50V (UK)	
C409	1-124-918-11	ELECT	47uF	20%	63V	
						(Canadian, E, AEP, G)
C410	1-124-910-11	ELECT	47uF	20%	50V (UK)	
C410	1-124-918-11	ELECT	47uF	20%	63V	
						(Canadian, E, AEP, G)
C413	1-126-103-11	ELECT	470uF	20%	16V	
C414	1-126-103-11	ELECT	470uF	20%	16V	
C430	1-102-816-00	CERAMIC	120PF	5%	50V (G)	
C431	1-162-282-31	CERAMIC	100PF	5%	50V (G)	
C451	1-101-361-00	CERAMIC	150PF	5%	50V	
						(Canadian, E, AEP)
C451	1-102-973-00	CERAMIC	100PF	5%	50V (G)	
C451	1-104-282-11	POLYSTYRENE	150PF	5%	50V (UK)	
C452	1-123-369-00	ELECT	4.7uF	20%	50V	
C453	1-124-472-11	ELECT	470uF	20%	10V	
						(Canadian, E, AEP)
C453	1-126-103-11	ELECT	470uF	20%	10V (UK, G)	
C454	1-130-341-00	FILM	0.056uF	3%	100V (UK)	
C454	1-136-162-00	FILM	0.056uF	5%	50V	
						(Canadian, E, AEP, G)
C455	1-130-971-00	FILM	0.016uF	3%	100V (UK)	
C455	1-136-032-11	FILM	0.016uF	5%	50V	
						(Canadian, E, AEP, G)
C457	1-130-479-00	MYLAR	0.0047uF	5%	50V	
C458	1-124-915-11	ELECT	10uF	20%	63V	
						(Canadian, E, AEP, G)
C458	1-126-059-11	ELECT	10uF	20%	50V (UK)	
C480	1-102-816-00	CERAMIC	120PF	5%	50V (G)	
C481	1-162-282-31	CERAMIC	100PF	5%	50V (G)	
⚠C501	1-161-744-00	CERAMIC	0.01uF		400V	
						(Canadian, E)
⚠C901	1-161-744-00	CERAMIC	0.01uF		400V	
						(AEP, UK, G)
C902	1-136-153-00	FILM	0.01uF	5%	50V (UK)	
C903	1-136-153-00	FILM	0.01uF	5%	50V (UK)	

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.	Les composants identifiés par une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une piéce portant le numéro spécifié.

Ref. No.	Part No.	Description				Remark
C904	1-102-978-00	CERAMIC	220PF	5%	50V (G)	
C952	1-136-153-00	FILM	0.01uF	5%	50V (UK)	
C953	1-136-153-00	FILM	0.01uF	5%	50V (UK)	
C954	1-102-978-00	CERAMIC	220PF	5%	50V (G)	
		< CONNECTOR >				
* CN1	1-561-651-00	SOCKET, CONNECTOR 7P				
* CN2	1-561-651-00	SOCKET, CONNECTOR 7P				
* CN3	1-568-118-11	SOCKET, CONNECTOR 16P				
* CN4	1-562-334-00	SOCKET, CONNECTOR 10P				
* CN5	1-561-651-00	SOCKET, CONNECTOR 7P				
CN6	1-568-203-11	PIN, CONNECTOR (PC BOARD) 11P				
CN7	1-568-203-11	PIN, CONNECTOR (PC BOARD) 11P				
* CN8	1-563-381-11	SOCKET, CONNECTOR 11P				
* CN9	1-566-451-11	HOUSING, CONNECTOR 3P				
* CN10	1-563-381-11	SOCKET, CONNECTOR 11P				
CN11	1-568-117-11	SOCKET, CONNECTOR 14P				
* CN12	1-565-484-11	CONNECTOR, BOARD TO BOARD 8P				
⚠CNJ501	1-540-041-21	OUTLET, AC (AC OUTLET) (E)				
⚠CNJ501	1-540-062-31	OUTLET, AC (AC OUTLET) (Canadian)				
* CNP604	1-508-694-00	SOCKET, CONNECTOR 8P				
* CP1	1-560-532-00	PIN, CONNECTOR 7P (AEP, UK, G)				
* CP2	1-560-532-00	PIN, CONNECTOR 7P				
* CP3	1-560-532-00	PIN, CONNECTOR 7P (AEP, UK, G)				
* CP3	1-568-204-11	PIN, CONNECTOR 16P				
* CP3	1-569-648-11	PIN, CONNECTOR 11P (Canadian, E)				
* CP4	1-568-202-11	PIN, CONNECTOR (PC BOARD) 10P				
CP5	1-568-120-11	PIN, CONNECTOR (PC BOARD) 7P				
CP6	1-568-120-11	PIN, CONNECTOR (PC BOARD) 7P				
		< DIODE >				
D201	8-719-912-20	DIODE	1SS120			
D202	8-719-912-20	DIODE	1SS120			
D203	8-719-303-00	LED	SEL2510C			
D204	8-719-303-00	LED	SEL2510C			
D205	8-719-303-00	LED	SEL2510C			
D206	8-719-302-23	DIODE	SEL2213C-C			
D207	8-719-302-23	DIODE	SEL2213C-C			
D208	8-719-301-52	LED	SEL2810A-C (SOURCE DIRECT)			
D209	8-719-301-52	LED	SEL2810A-C (MUTING -20dB)			
D301	8-719-230-02	DIODE	30DF2			
D302	8-719-230-02	DIODE	30DF2			
D303	8-719-230-02	DIODE	30DF2			
D304	8-719-230-02	DIODE	30DF2			
D305	8-719-200-77	DIODE	10E2N			
D306	8-719-200-77	DIODE	10E2N			
D307	8-719-200-77	DIODE	10E2N			
D308	8-719-200-77	DIODE	10E2N			
D309	8-719-200-77	DIODE	10E2N			
D310	8-719-200-77	DIODE	10E2N			
D311	8-719-200-77	DIODE	10E2N			
D312	8-719-912-20	DIODE	1SS120			
D313	8-719-912-20	DIODE	1SS120			
D314	8-719-912-20	DIODE	1SS120			
D319	8-719-912-20	DIODE	1SS120			
D320	8-719-912-20	DIODE	1SS120			
D362	8-719-912-20	DIODE	1SS120			
D363	8-719-912-20	DIODE	1SS120			
D364	8-719-912-20	DIODE	1SS120			
D401	8-719-000-84	DIODE	UZL-7M1			
		< CONNECTOR >				
* EH2	1-564-508-11	PLUG, CONNECTOR 5P				
* EH3	1-564-508-11	PLUG, CONNECTOR 5P				
EH4	1-564-511-11	PLUG, CONNECTOR 8P				
		< FUSE >				
⚠F501	1-532-350-00	FUSE, TIME-LAG 4A (E)				
⚠F501	1-532-510-00	FUSE, GLASE TUBE 8A (Canadian)				
⚠F502	1-532-350-00	FUSE, TIME-LAG 4A (E)				
⚠F901	1-532-350-00	FUSE, TIME-LAG 4A (AEP, UK, G)				
		< IC >				
IC301	8-749-920-70	IC	STK-3102-3			
IC302	8-759-111-68	IC	uPC1237HA			
IC401	8-759-745-60	IC	NJM4560D			
IC402	8-759-231-59	IC	M5F7815L			
IC403	8-759-245-87	IC	M5F7915L			
		< JACK >				
J101	1-580-028-11	JACK, PIN 6P (TUNER, CD, TAPE1 REC OUT)				
J102	1-580-027-11	JACK, PIN 6P (TAPE1/TAPE2 IN, TAPE2 REC OUT)				
J103	1-580-028-11	JACK, PIN 6P (DIRECT IN, ADAPTOR IN/OUT)				
J104	1-568-250-11	JACK, PIN 2P (PHONO) (Canadian, E, AEP, G)				
J104	1-568-250-21	JACK, PIN 2P (PHONO) (UK)				
J501	1-507-863-51	JACK, PHONE (HEADPHONES)				
		< COIL >				
L301	1-420-872-00	COIL, AIR CORE				
L351	1-420-872-00	COIL, AIR CORE				
L401	1-413-101-00	COIL INPUT (G)				
L402	1-413-101-00	COIL INPUT (G)				
L451	1-413-101-00	COIL INPUT (G)				
L452	1-413-101-00	COIL INPUT (G)				
		< TRANSISTOR >				
Q201	8-729-140-96	TRANSISTOR	KSC1008			
Q202	8-729-194-57	TRANSISTOR	2SC945-P			
Q203	8-729-141-03	TRANSISTOR	2SA733-QP			

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.	Les composants identifiés par une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une piéce portant le numéro spécifié.

Ref. No.	Part No.	Description	Remark
Q204	8-729-141-03	TRANSISTOR 2SA733-QP	
Q301	8-729-203-45	TRANSISTOR 2SC3423-O	
Q302	8-729-127-53	TRANSISTOR 2SC2275-P	
Q303	8-729-141-10	TRANSISTOR 2SA985A	
Q304	8-729-320-03	TRANSISTOR 2SC2921M-O	
Q305	8-729-320-01	TRANSISTOR 2SA1215M-O	
Q306	8-729-140-82	TRANSISTOR 2SA988-PAFAEA	
Q351	8-729-203-45	TRANSISTOR 2SC3423-O	
Q352	8-729-127-53	TRANSISTOR 2SC2275-P	
Q353	8-729-141-10	TRANSISTOR 2SA985A	
Q354	8-729-320-03	TRANSISTOR 2SC2921M-O	
Q355	8-729-320-01	TRANSISTOR 2SA1215M-O	
Q356	8-729-140-82	TRANSISTOR 2SA988-PAFAEA	
Q401	8-729-354-52	TRANSISTOR 2SC2545	
Q402	8-729-354-52	TRANSISTOR 2SC2545	
Q451	8-729-354-52	TRANSISTOR 2SC2545	
Q452	8-729-354-52	TRANSISTOR 2SC2545	
		< RESISTOR >	
R000	1-247-725-11	CARBON 10K 5% 1/4W	
R101	1-246-545-00	CARBON 1.0M 5% 1/4W	
R102	1-246-545-00	CARBON 1.0M 5% 1/4W	
R103	1-246-545-00	CARBON 1.0M 5% 1/4W	
R104	1-246-545-00	CARBON 1.0M 5% 1/4W	
R105	1-247-713-11	CARBON 1K 5% 1/4W	F
R106	1-249-417-11	CARBON 1K 5% 1/4W	F
R107	1-246-545-00	CARBON 1.0M 5% 1/4W	
R108	1-259-500-11	CARBON 1M 5% 1/6W	
R109	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R110	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R111	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R112	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R113	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R114	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R151	1-246-545-00	CARBON 1.0M 5% 1/4W	
R152	1-246-545-00	CARBON 1.0M 5% 1/4W	
R153	1-246-545-00	CARBON 1.0M 5% 1/4W	
R154	1-246-545-00	CARBON 1.0M 5% 1/4W	
R155	1-247-713-11	CARBON 1K 5% 1/4W	F
R156	1-249-417-11	CARBON 1K 5% 1/4W	F
R157	1-246-545-00	CARBON 1.0M 5% 1/4W	
R158	1-259-500-11	CARBON 1M 5% 1/6W	
R159	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R160	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R161	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R162	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R163	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R164	1-249-417-11	CARBON 1K 5% 1/4W	(G)
R201	1-249-417-11	CARBON 1K 5% 1/4W	F
R202	1-247-700-11	CARBON 100 5% 1/4W	

Ref. No.	Part No.	Description	Remark
R203	1-247-717-11	CARBON 2.2K 5% 1/4W	F
R204	1-247-722-11	CARBON 5.6K 5% 1/4W	
R205	1-249-753-15	CARBON 4.7M 5% 1/4W	
R206	1-249-753-15	CARBON 4.7M 5% 1/4W	
R208	1-247-170-00	CARBON 43K 5% 1/4W	
R209	1-247-152-00	CARBON 7.5K 5% 1/4W	
R210	1-249-464-11	CARBON 39K 5% 1/4W	
R211	1-249-465-11	CARBON 47K 5% 1/4W	
R212	1-249-465-11	CARBON 47K 5% 1/4W	
R213	1-247-722-11	CARBON 5.6K 5% 1/4W	
R214	1-247-693-11	CARBON 27 5% 1/4W	
R215	1-247-754-11	CARBON 1.5K 5% 1/2W	
R216	1-247-754-11	CARBON 1.5K 5% 1/2W	
R217	1-247-750-11	CARBON 680 5% 1/2W	
R218	1-249-462-11	CARBON 22K 5% 1/4W	
R219	1-249-465-11	CARBON 47K 5% 1/4W	
R220	1-247-749-11	CARBON 560 5% 1/2W	
R221	1-247-717-11	CARBON 2.2K 5% 1/4W	F
R222	1-247-725-11	CARBON 10K 5% 1/4W	
R223	1-249-465-11	CARBON 47K 5% 1/4W	
R224	1-247-721-11	CARBON 4.7K 5% 1/4W	
⚠R225	1-247-743-11	CARBON 220 5% 1/2W	F
⚠R226	1-215-892-11	METAL OXIDE 1K 5% 2W	F
⚠R227	1-215-892-11	METAL OXIDE 1K 5% 2W	F
R251	1-249-417-11	CARBON 1K 5% 1/4W	F
R252	1-247-700-11	CARBON 100 5% 1/4W	
R253	1-247-717-11	CARBON 2.2K 5% 1/4W	F
R254	1-247-722-11	CARBON 5.6K 5% 1/4W	
R255	1-249-753-15	CARBON 4.7M 5% 1/4W	
R256	1-249-753-15	CARBON 4.7M 5% 1/4W	
R258	1-247-170-00	CARBON 43K 5% 1/4W	
R259	1-247-152-00	CARBON 7.5K 5% 1/4W	
R260	1-249-464-11	CARBON 39K 5% 1/4W	
R261	1-249-465-11	CARBON 47K 5% 1/4W	
R262	1-249-465-11	CARBON 47K 5% 1/4W	
R263	1-247-722-11	CARBON 5.6K 5% 1/4W	
R301	1-247-713-11	CARBON 1K 5% 1/4W	F
R302	1-249-599-11	CARBON 91K 5% 1/4W	
R303	1-249-668-11	CARBON 620 5% 1/2W	
R304	1-247-713-11	CARBON 1K 5% 1/4W	F (E, AEP1, UK, G)
R304	1-249-417-11	CARBON 1K 5% 1/4W	(Canadian, AEP2)
R305	1-247-707-11	CARBON 390 5% 1/4W	(E, AEP1, UK, G)
R305	1-249-412-11	CARBON 390 5% 1/4W	(Canadian, AEP2)
⚠R306	1-212-990-00	FUSIBLE 220 5% 1/2W	F
⚠R307	1-212-950-00	FUSIBLE 4.7 5% 1/2W	F
⚠R308	1-212-950-00	FUSIBLE 4.7 5% 1/2W	F
R309	1-217-611-00	RES, METAL PLATE 0.1	

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.	Les composants identifiés par une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une piéce portant le numéro spécifié.

Ref. No.	Part No.	Description				Remark
R310	1-217-611-00	RES, METAL PLATE	0.1			
⚠R311	1-247-717-11	CARBON	2.2K	5%	1/4W	F
R312	1-249-460-11	CARBON	15K	5%	1/4W	
⚠R313	1-212-962-00	FUSIBLE	15	5%	1/2W	F
⚠R314	1-212-962-00	FUSIBLE	15	5%	1/2W	F
R315	1-247-891-00	CARBON	330K	5%	1/4W	
R316	1-247-725-11	CARBON	10K	5%	1/4W	
R317	1-247-887-00	CARBON	220K	5%	1/4W	
R318	1-247-881-00	CARBON	120K	5%	1/4W	
R319	1-249-461-11	CARBON	18K	5%	1/4W	
R320	1-247-721-11	CARBON	4.7K	5%	1/4W	
R321	1-249-462-11	CARBON	22K	5%	1/4W	
⚠R323	1-212-849-00	FUSIBLE	4.7	5%	1/4W	F
R324	1-247-727-11	CARBON	10	5%	1/2W	
R325	1-247-747-11	CARBON	470	5%	1/2W	
R326	1-249-721-11	CARBON	100K	5%	1/2W	
R327	1-247-708-11	CARBON	470	5%	1/4W	
R351	1-247-713-11	CARBON	1K	5%	1/4W	F
R352	1-249-599-11	CARBON	91K	5%	1/4W	
R353	1-249-668-11	CARBON	620	5%	1/2W	
R354	1-247-713-11	CARBON	1K	5%	1/4W	F (E, AEP1, UK, G)
R354	1-249-417-11	CARBON	1K	5%	1/4W	(Canadian, AEP2)
R355	1-247-707-11	CARBON	390	5%	1/4W	(E, AEP1, UK, G)
R355	1-249-412-11	CARBON	390	5%	1/4W	(Canadian, AEP2)
⚠R356	1-212-990-00	FUSIBLE	220	5%	1/2W	F
⚠R357	1-212-950-00	FUSIBLE	4.7	5%	1/2W	F
⚠R358	1-212-950-00	FUSIBLE	4.7	5%	1/2W	F
R359	1-217-611-00	RES, METAL PLATE	0.1			
R360	1-217-611-00	RES, METAL PLATE	0.1			
⚠R361	1-247-717-11	CARBON	2.2K	5%	1/4W	F
R362	1-249-460-11	CARBON	15K	5%	1/4W	
⚠R363	1-212-962-00	FUSIBLE	15	5%	1/2W	F
⚠R364	1-212-962-00	FUSIBLE	15	5%	1/2W	F
R365	1-247-891-00	CARBON	330K	5%	1/4W	
R374	1-247-727-11	CARBON	10	5%	1/2W	
R375	1-247-747-11	CARBON	470	5%	1/2W	
R376	1-249-721-11	CARBON	100K	5%	1/2W	
R377	1-247-708-11	CARBON	470	5%	1/4W	
⚠R401	1-216-459-00	METAL OXIDE	2.7K	5%	2W	F
⚠R402	1-215-895-11	METAL OXIDE	3.3K	5%	2W	F
R405	1-247-706-11	CARBON	330	5%	1/4W	F (Canadian, E, AEP, UK)
R406	1-249-469-11	CARBON	100K	5%	1/4W	
R407	1-247-700-11	CARBON	100	5%	1/4W	
R408	1-249-469-11	CARBON	100K	5%	1/4W	
R409	1-247-713-11	CARBON	1K	5%	1/4W	F
R410	1-247-713-11	CARBON	1K	5%	1/4W	F
R411	1-247-725-11	CARBON	10K	5%	1/4W	
R412	1-249-484-11	CARBON	6.8	5%	1/2W	
R413	1-247-739-11	CARBON	100	5%	1/2W	
R414	1-247-138-00	CARBON	2K	5%	1/4W	
R415	1-247-700-11	CARBON	100	5%	1/4W	
R416	1-214-937-00	METAL	1M	1%	1/2W	
R417	1-249-844-11	CARBON	56K	5%	1/2W	
R418	1-249-818-11	CARBON	4.7K	1%	1/2W	
R419	1-247-713-11	CARBON	1K	5%	1/4W	F (Canadian, E, AEP, UK)
R431	1-247-713-11	CARBON	1K	5%	1/4W	(G)
R432	1-247-713-11	CARBON	1K	5%	1/4W	(G)
R455	1-247-706-11	CARBON	330	5%	1/4W	F (Canadian, E, AEP, UK)
R456	1-249-469-11	CARBON	100K	5%	1/4W	
R457	1-247-700-11	CARBON	100	5%	1/4W	
R458	1-249-469-11	CARBON	100K	5%	1/4W	
R459	1-247-713-11	CARBON	1K	5%	1/4W	F
R460	1-247-713-11	CARBON	1K	5%	1/4W	F
R461	1-247-725-11	CARBON	10K	5%	1/4W	
R462	1-249-484-11	CARBON	6.8	5%	1/2W	
R463	1-247-739-11	CARBON	100	5%	1/2W	
R465	1-247-700-11	CARBON	100	5%	1/4W	
R466	1-214-937-00	METAL	1M	1%	1/2W	
R467	1-249-844-11	CARBON	56K	5%	1/2W	
R468	1-249-818-11	CARBON	4.7K	1%	1/2W	
R469	1-247-713-11	CARBON	1K	5%	1/4W	F
R481	1-247-713-11	CARBON	1K	5%	1/4W	(G)
R482	1-247-713-11	CARBON	1K	5%	1/4W	(G)
R902	1-247-727-11	CARBON	10	5%	1/2W	(G)
R903	1-247-727-11	CARBON	10	5%	1/2W	(G)
R952	1-247-727-11	CARBON	10	5%	1/2W	(G)
R953	1-247-727-11	CARBON	10	5%	1/2W	(G)

< VARIABLE RESISTOR >

RT301	1-237-455-11	RES, ADJ, CARBON	500
RT351	1-237-455-11	RES, ADJ, CARBON	500
RV101	1-238-448-11	RES, VAR, CARBON	150K/150K (BALANCE)
RV102	1-238-446-11	RES, VAR, CARBON	250K/250K (TREBLE)
RV103	1-238-447-11	RES, VAR, CARBON	25K/500K (BASS)
RV104	1-237-472-11	RES, VAR, CARBON	120K/120K (ATTENUATOR)

< RELAY >

RY301	1-515-676-11	RELAY
RY302	1-515-676-11	RELAY

< SWITCH >

S201	1-571-824-11	SWITCH, ROTARY (INPUT SELECTOR)
S202	1-571-826-11	SWITCH, ROTARY (INPUT SELECTOR)
S203	1-571-823-11	SWITCH, ROTARY SLIDE (REC OUT SELECTOR)

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.	Les composants identifiés par une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une piéce portant le numéro spécifié.

Ref. No.	Part No.	Description	Remark
S204	1-571-828-11	SWITCH, PUSH (1 KEY) (SOURCE DIRECT)	
S205	1-571-827-11	SWITCH, PUSH (1 KEY) (MUTING)	
S206	1-571-822-11	SWITCH, ROTARY SLIDE (SPEAKER)	
S207	1-571-825-11	SWITCH, ROTARY (MODE)	
S401	1-571-111-11	SWITCH, PUSH (1 KEY) (CARTRIDGE)	
⚠S501	1-554-920-11	SWITCH, PUSH (AC POWER) (1 KEY) (POWER)	
⚠S702	1-570-307-11	SWITCH, VOLTAGE CHANGE (VOLTAGE SELECTOR)	(E)
		< TRANSFORMER >	
⚠T1	1-449-685-11	TRANSFORMER, POWER (Canadian)	
⚠T1	1-449-687-11	TRANSFORMER, POWER (G)	
⚠T1	1-449-688-11	TRANSFORMER, POWER (AEP)	
⚠T1	1-449-689-11	TRANSFORMER, POWER (UK)	
⚠T1	1-449-690-11	TRANSFORMER, POWER (E)	
		< TERMINAL >	
TM501	1-537-227-11	TERMINAL BOARD (SP) (SPEAKER) (AEP2)	
TM501	1-537-228-11	TERMINAL BOARD (SP) (SPEAKER) (G)	
TM501	1-537-235-11	TERMINAL BOARD (SP) (SPEAKER)	(Canadian, E, AEP1, UK)
		< TEST PIN >	
* TP301	1-535-135-00	BASE POST 14MM (10MM PITCH) 2P	
* TP351	1-535-135-00	BASE POST 14MM (10MM PITCH) 2P	
		< CONNECTOR >	
* VH2	1-535-139-00	BASE POST 14MM (10MM PITCH) 2P	
* VH3	1-535-139-00	BASE POST 14MM (10MM PITCH) 2P	
* VH4	1-564-321-00	PIN, CONNECTOR 2P (AEP, UK, G)	
* VH5	1-565-792-11	PIN, CONNECTOR 2P	
* VH6	1-564-321-00	PIN, CONNECTOR 2P (AEP, UK, G)	
* VH8	1-564-241-00	PIN, CONNECTOR 4P	
* VH9	1-560-595-21	TERMINAL (WITH BASS) (E)	
* VH9	1-564-321-00	PIN, CONNECTOR 2P (Canadian)	
* VH10	1-565-792-11	PIN, CONNECTOR 2P (Canadian, E)	
* VH11	1-564-321-00	PIN, CONNECTOR 2P (Canadian, E)	
* VH12	1-564-320-00	PIN, CONNECTOR 2P	
* VH15	1-565-792-11	PIN, CONNECTOR 2P	
* VH20	1-535-141-00	BASE POST 22MM (10MM PITCH) 4P (E)	

****

The components identified by mark ⚠ or dotted line with mark ⚠ are critical for safety. Replace only with part number specified.	Les composants identifiés par une marque ⚠ sont critiques pour la sécurité. Ne les remplacer que par une piéce portant le numéro spécifié.

9-953-786-81

Sony Corporation
Audio Group

English
93H0972-1
Printed in Japan

Published by Audio Sector Quality Assurance Dept.